



# Intel<sup>®</sup> Ethernet NVM Update Tool

Quick Usage Guide for EFI

---

Ethernet Products Group (EPG)

*October 2020*

Revision 1.3  
332160-004

## Revision History

---

Revision	Date	Comments
1.3	October 12, 2020	Updates include the following: <ul style="list-style-type: none"><li>• Updates for Intel® Ethernet Controller E810.</li></ul>
1.2	November 19, 2018	Updates include the following: <ul style="list-style-type: none"><li>• Updates for NVM version 6.80 for Intel® Ethernet Controller X710/XXV710/XL710.</li><li>• Updates for NVM version 2.00 for Intel® Ethernet Controller X550.</li><li>• Added <a href="#">Section 5.1, "Troubleshooting"</a>.</li><li>• Added <a href="#">Section 5.2, "Recovery Mode"</a>.</li><li>• Added <a href="#">Section 6.0, "Create/Edit <code>nvmupdate.cfg</code> for Custom NVM Images"</a>.</li></ul>
1.1	February 10, 2016	Updates for Software Release 5 for i40e and EFI.
1.0	March 4, 2020	Initial public release.

## Contents

---

<b>1.0</b>	<b>Introduction</b>	<b>5</b>
<b>2.0</b>	<b>Update Both NVM and Driver at the Same Time</b>	<b>5</b>
<b>3.0</b>	<b>Obtaining New Images</b>	<b>5</b>
<b>4.0</b>	<b>Preparing for the Update</b>	<b>6</b>
<b>5.0</b>	<b>Running the NVM Update Tool</b>	<b>7</b>
5.1	Troubleshooting	8
5.1.1	Troubleshooting Using Debug Logs	9
5.2	Recovery Mode	9
<b>6.0</b>	<b>Create/Edit <i>nvmupdate.cfg</i> for Custom NVM Images</b>	<b>10</b>
6.1	Sample Configuration File Template	10
6.2	Device Block in the Configuration File	10
6.3	Steps to Create/Edit <i>nvmupdate.cfg</i> File to Update Custom NVM Image	11
6.3.1	On E810 Devices	11
6.3.2	On X710/XXV710/XL710 and X550 Devices	12
<b>7.0</b>	<b>Summary</b>	<b>14</b>



**NOTE:**      *This page intentionally left blank.*

## 1.0 Introduction

This document demonstrates how to update both the Non-Volatile Memory (NVM) and drivers on the Intel® Ethernet Controller E810 (E810), the Intel® Ethernet Controller X710/XXV710/XL710 (X710/XXV710/XL710), the Intel® Ethernet Controller X550 (X550), and the Intel® Ethernet Converged Network Adapters using the Intel® Ethernet NVM Update Tool (NVM Update Tool). It is a guide to servicing NVM images, firmware, and drivers of the E810, X710/XXV710/XL710, and X550 by customers and service technicians in the field.

**Note:** The information in this document is for experienced system administrators who are familiar with server, network, and data center concepts and technologies.

## 2.0 Update Both NVM and Driver at the Same Time

Keeping up with software changes, performance enhancements, or security updates requires the most current hardware drivers for supported systems. Previous updates to Intel network adapters were driver specific. With E810, X710/XXV710/XL710, and X550 adapters, both the firmware (device NVM image) and network drivers are field-serviceable, allowing the NVM image and network driver to be updated as a matched set. Updating the device image and driver together can increase key features including performance, manageability, media types, physical port counts, virtualization, offloads, remote boot options, VLAN support, teaming, and Receive Side Scaling.

**Note:** The EFI version of the NVM Update Tool allows the NVM update without updating to the most current *ice* and *i40e* drivers. It is recommended that the most current *ice* and *i40e* drivers be installed once the system has been booted into its running operating system.

The NVM Update Tool has a built-in integrity check that ensures only Intel-approved firmware updates on the E810, X710/XXV710/XL710, and X550 devices. Integrity validation of NVM updates is provided by a digital signature. NVM updates are validated prior to invalidating the old NVM configuration, so the old NVM and the configuration are still usable should the update fail.

**Note:** On X710/XXV710/XL710 and X550 devices, updating to the most current NVM (with the NVM Update Package) and driver does not update the Option ROM. Intel recommends an Option ROM update after the NVM and driver are updated. Refer to the [User Guides for Intel® Ethernet Adapters](#) page for the most current Option ROM update process version.

**Note:** When running SR-IOV, it is recommended that all Virtual Functions be disabled prior to the NVM Update process.

## 3.0 Obtaining New Images

The [Intel Download Center](#) (E810, X710, XXV710, XL710, or X550) is Intel's repository for the latest software and drivers for Intel products. The NVM Update Packages for Windows, Linux, ESX, FreeBSD, and EFI/EFI2 are located at:

Intel® Ethernet Network Adapter E810 Series	<a href="https://downloadcenter.intel.com/download/29736">https://downloadcenter.intel.com/download/29736</a>
Intel® Ethernet Network Adapter 700 Series	<a href="https://downloadcenter.intel.com/download/24769">https://downloadcenter.intel.com/download/24769</a>
Intel® Ethernet Network Adapter X550 Series	<a href="https://downloadcenter.intel.com/download/28336">https://downloadcenter.intel.com/download/28336</a>

Use the Software/NVM matrix tables in the [Intel® Ethernet Controller E810 Feature Support Matrix](#), the [Intel® Ethernet Controller X710/XXV710/XL710 Feature Support Matrix](#), and the [Intel® Ethernet Controller X550 Feature Support Matrix](#) to ensure firmware image and driver compatibility. These documents are continuously maintained and always up-to-date.

## 4.0 Preparing for the Update

Download the package of the NVM Update Tool, and perform the following steps:

1. Unzip the package contents to a flash drive or CD-ROM.
2. Insert the flash drive or CD-ROM into the system of the adapter to be updated.
3. Boot the system to the EFI shell.
4. Navigate to the correct location of the NUP tool executable and binary files as shown in [Figure 1](#).

```

UEFI Interactive Shell v2.2
EDK II
UEFI v2.70 (American Megatrends, 0x0005000E)
Mapping table
  FS1: Alias(s):HD1b65535a1:;BLK6:
        PciRoot(0x0)/Pci(0x17,0x0)/Sata(0x1,0xFFFF,0x0)/HD(1,GPT,99C3FE3D-D4C6-45A9-999D-3827F50
EA1,0x800,0x100000)
  FS0: Alias(s):HD0f0b:;BLK2:
        PciRoot(0x0)/Pci(0x14,0x0)/USB(0x5,0x0)/HD(1,MBR,0x15A5BE95,0x800,0x77F800)
  BLK0: Alias(s):
        PciRoot(0x0)/Pci(0x14,0x0)/USB(0x13,0x0)
  BLK8: Alias(s):
        PciRoot(0x0)/Pci(0x1C,0x4)/Pci(0x0,0x4)/USB(0x0,0x0)
  BLK9: Alias(s):
        PciRoot(0x0)/Pci(0x1C,0x4)/Pci(0x0,0x4)/USB(0x1,0x0)
  BLK3: Alias(s):
        PciRoot(0x0)/Pci(0x17,0x0)/Sata(0x0,0xFFFF,0x0)
  BLK5: Alias(s):
        PciRoot(0x0)/Pci(0x17,0x0)/Sata(0x1,0xFFFF,0x0)
  BLK4: Alias(s):
        PciRoot(0x0)/Pci(0x17,0x0)/Sata(0x0,0xFFFF,0x0)/HD(1,GPT,E33237BD-DD6D-4F76-AC2E-22CD227
EB4,0x800,0x2E938800)
  BLK7: Alias(s):
        PciRoot(0x0)/Pci(0x17,0x0)/Sata(0x1,0xFFFF,0x0)/HD(2,GPT,20C9D643-DCB9-4820-B115-727A206
432,0x100800,0x37D42800)
  BLK1: Alias(s):
        PciRoot(0x0)/Pci(0x14,0x0)/USB(0x5,0x0)
Press ESC in 1 seconds to skip startup.nsh or any other key to continue.
Shell> fs0:
FS0:\> cd \E810\EFI2x64
FS0:\E810\EFI2x64\> nvupdate64e.efi_

```

**Figure 1. NUP Tool Executable and Binary Files**

## 5.0 Running the NVM Update Tool

The NVM Update Tool runs from a Command-Line Interface (CLI). There are optional CLI attributes for specific tasks and are recommended for advanced users only. As CLI syntax, the NVM Update Tool can be scripted to run across large environments. An example of the update syntax is as follows:

```
nvmupdate64e.efi - command syntax  
nvmupdate64e.efi -l fileoutput.txt - command with optional attribute
```

**Note:** For assistance with optional CLI attributes, contact your Intel Representative.

Run the tool like any CLI executable. An example of the EFI CLI version of the NVM Update Tool update and its output is shown in [Figure 2](#).

**Note:** A typical update takes several minutes to complete.

```
NVMUpdate version 1.35.33.4  
Copyright (C) 2013 - 2020 Intel Corporation.  
  
WARNING: To avoid damage to your device, do not stop the update or reboot or power off the system  
ring this update.  
Inventory in progress. Please wait [***|.....]  
  
Num Description                               Ver.(hex)  DevId S:B   Status  
=== =====  
01) Intel(R) Ethernet Network Adapter         1.64(1.40)  1592 00:024 Update  
     E810-C-Q2                                 available  
  
Options: Adapter Index List (comma-separated), [A]ll, e[X]it  
Enter selection: a  
Would you like to back up the NVM images? [Y]es/[N]o: n  
Update in progress. This operation may take several minutes.  
[**~.....]  
  
Num Description                               Ver.(hex)  DevId S:B   Status  
=== =====  
01) Intel(R) Ethernet Network Adapter         2.00(2.00)  1592 00:024 Update  
     E810-C-Q2                                 successful  
  
Reboot is required to complete the update process.  
  
Tool execution completed with the following status: All operations completed successfully.  
Press any key to exit.  
FS0:\E810\EFI2x64\> _
```

**Figure 2. Example Update and Output**

**Note:** The NVM update may require a two-step process depending on the initial image revision. Use the Software/NVM Compatibility table to verify the latest image versions.

When the flash image write completes, the tool asks for a reboot of the system to complete the update process and load the new firmware. After the reboot, boot the host into the intended operating system, and update the network adapter to the most current driver.

**Note:** When updating from early NVM images, the NVM Update Tool may indicate that a power-cycle of the system is necessary.

**Note:** The tool allows for updating one, multiple, or all of the installed adapters. For example, to update NVM firmware for two of three installed adapters, follow the syntax as shown in the example below. Enter selection 02,03 (separated by a commas).

```

Num Description                               Ver. DevId S:B   Status
=====
01) Intel(R) Ethernet Converged Network      1.147 1563 00:004 Update not available
Adapter X550-T2
02) Intel(R) Ethernet Network Adapter        5.81 158B 00:006 Update available
XXV710-2
03) Intel(R) Ethernet Converged Network      5.05 1583 00:131 Update available
Adapter XL710-Q2

Options: Adapter Index List (comma-separated), [A]ll, e[X]it
Enter selection:02,03
Would you like to back up the NVM images? [Y]es/[N]o: n
Update in progress. This operation may take several minutes.
[***+.....]
Reboot is required to complete the update process.

Tool execution completed with the following status: All operations completed successfully
Press any key to exit.

```

**Figure 3. Example for Updating Multiple Adapters**

**Note:** An NVM image downgrade process is available from Intel. Contact your Intel Representative for support of this process.

## 5.1 Troubleshooting

- Update to the most current base driver prior to running the NVM Update Tool to ensure the newest features of the NVM image can be installed.
- Refer to the “NVM and Software Compatibility” section in each of the following documents:
  - For the Intel® Ethernet Controller E810, refer to the [Intel® Ethernet Controller E810 Feature Support Matrix](#) (Doc ID: 630155).
  - For the Intel® Ethernet Controller X710/XXV710/XL710, refer to the [Intel® Ethernet Controller X710/XXV710/XL710 Feature Support Matrix](#) (Doc ID: 332191).
  - For the Intel® Ethernet Controller X550, refer to the [Intel® Ethernet Controller X550 Feature Support Matrix](#) (Doc ID: 335253).

The “Software/NVM Compatibility” tables indicate the set of NVM images and Intel® Ethernet Controller software releases that go together. Intel recommends that you update the NVM and Software driver to compatible versions.

The “NVM Transition Support” tables indicate the version of NVM from which the NVM Update Tool allows updates.

- In case of a security issue, the security revision might be incremented and then an NVM update to an older NVM with a lower security revision might not be allowed.



- The NVM version for the X550 is NOT shown in the GUI. Only the EEtrack ID is displayed. If you run **nvmupdate** with **-i**, the version is displayed.

### 5.1.1 Troubleshooting Using Debug Logs

1. Use the following command to get the log file if there is any error seen.

```
nvmupdate64e -l nvmupdate.log
```

This is a text file that contains history of the NVM Update Tool's execution, including the success or failure status for each operation, and what adapters and ORMs were discovered. After running this command, the tool creates the *nvmupdate.log* file under the same folder as *nvmupdate.cfg*. The log file is overwritten each time the NVM Update Tool is executed.

2. Use following command to get a little more information on what is in the system by using **nvmupdate** with an inventory mode.

```
nvmupdate64e -i -l inv.log
```

This provides more details about the adapters in the system to help narrow down the debug scope.

3. Use following command(s) to get a superset of debug logs.

First set following environment variables before **nvmupdate** execution. For debugging purposes, it is necessary to set these flags:

```
export NUL_DEBUGLOG=1  
export QV_DEBUG_LOG=0xFFFFFFFF
```

Now the log generated using the following command is much more detailed.

```
nvmupdate64e -l nvmupdate.lo
```

If you continue to have issues, contact Intel support with all these log files.

## 5.2 Recovery Mode

When using the NVM Update Tool, it is possible to get a status of "RECOVERY" or messages about Recovery Mode from the tool and/or Base Driver. If this occurs please refer to the [Recovery Mode for Intel® Ethernet Products Application Note](#) (Doc ID: 606286).

## 6.0 Create/Edit *nvmupdate.cfg* for Custom NVM Images

The goal of this section is to assist Intel Ethernet users to create/edit the *nvmupdate.cfg* file for their custom NVM images. For the E810, X710/XXV710/XL710, and X550 families of products, this allows the use of NVM Update utility to update custom NVM images that are not included in the NVM Updated packages posted by Intel.

### 6.1 Sample Configuration File Template

The following is an example of a configuration file with one device block:

```
=====
CURRENT FAMILY: 1.0.0
CONFIG VERSION: 1.20.0

; NIC device
BEGIN DEVICE
DEVICENAME: E810_CQDA2_O_SEC_FW
VENDOR: 8086
DEVICE: 1592
SUBVENDOR: 8086
SUBDEVICE: 0002
NVM IMAGE: E810_CQDA2_O_SEC_FW_1p4p1p13_NVM_2p0_PLDMoMCTP_80003D96_signed_pldm_fixed.bin
EEPID: 80003D96
SKIP NETLIST: FALSE
IMAGE DOWNGRADE: TRUE
RESET TYPE: REBOOT
CURRENT GFID: 0157-1590
ORIGINAL GFID: 0157-1590
REVISION: 02
; REPLACES: 80003D96
END DEVICE
=====
```

### 6.2 Device Block in the Configuration File

A device block in configuration file lists out following information:

- **CONFIG VERSION** — Version of syntax for the configuration file.
- **DEVICENAME** — Device name currently in use. For example, Intel X550 Adapter, etc.
- **VENDOR** — PCI vendor ID 8086 identifies Intel as the manufacturer of the device.
- **DEVICE** — Device ID. Device IDs for supported retail Intel Ethernet Adapters can be found in here: <https://www.intel.com/content/www/us/en/support/articles/000005612/network-and-i-o/ethernet-products.html>
- **SUBVENDOR** — Sub-vendor ID in hexadecimal format. This is optional when EEPROM ID is used.
  - On E810 NIC entries, this is a mandatory field.
  - On X710/XXV710/XL710 and X550 devices, this is optional when EEPROM ID is used.
- **SUBDEVICE** — Sub-device ID in hexadecimal format. This is optional when EEPROM ID is used.
  - On E810 NIC entries, this is a mandatory field.
  - On X710/XXV710/XL710 and X550 devices, this is optional when EEPROM ID is used.
- **NVM IMAGE** — NVM Image binary file name with which to update.

- **OROM IMAGE** — OROM Image file name.
- **EEPID** — ETrack ID of NVM Image with which to update.
- **REPLACES** — ETrack ID of NVM Image that with which to replace. Multiple ETrack IDs can be entered, separated by spaces.
  - On E810 NIC entries, the tool compares 4-part ID, which makes this field optional.
- **RESET TYPE** — Specifies whether reboot/power cycle is required to complete the NVM update process.
- **REVISION** — Revision number in hexadecimal format.
  - On E810 NIC devices, this field differentiates between B0 and C0 devices.
  - This is optional on X710/XXV710/XL710 and X550 devices.
- **CURRENT GFID** — On E810 devices, the value consists of Intel IANA and Silicon default Device ID. If this field is not present but **ORIGINAL GFID** is, the tool uses **ORIGINAL GFID** value for both cases. This is important to reduce the time required for update to complete.
- **ORIGINAL GFID** — On E810 devices, the value consists of Intel IANA and Silicon default Device ID. If this field is not present but **CURRENT GFID** is, the tool uses **CURRENT GFID** value for both cases. This is important to reduce the time required for update to complete.

## 6.3 Steps to Create/Edit *nvmupdate.cfg* File to Update Custom NVM Image

### 6.3.1 On E810 Devices

1. Include the custom NVM Image binary file under the same folder as the *nvmupdate.cfg* file and *nvmupdate64e* executable file.
2. Open the *nvmupdate.cfg* file as text file.
3. Copy and paste one of the device blocks (or use the example in [Section 6.1](#)) and update following information for custom NVM image update.
  - a. Custom NVM Image binary file name in **NVM IMAGE** field.
  - b. ETrack ID (in the **EEPID** field) of the custom NVM Image listed in **NVM IMAGE** field. This is the image that the device will be update to.
  - c. ETrack ID (in **REPLACES** field) of NVM Image that an update will be allowed from applies only for LOM designs, and is not needed for NIC devices.

**Note:** When editing the *nvmupdate.cfg* file, if there is a need to have ETrack ID in the **REPLACES** field, you must ensure that this ETrack ID and the **EEPID** field are the same type of image and are both created for the device that is being updated.

- d. **DEVICE, VENDOR, SUBDEVICE, and SUBVENDOR** must be set correctly to match the device required to update.

The remaining fields (including **CURRENT FAMILY, CONFIG VERSION, DEVICENAME, and RESET TYPE**) can typically be left as is.

4. Run the *nvmupdate64e* executable file.

Following is an example of Device block in the configuration file. This includes the minimum fields required for an update. The fields listed in red should be updated:

```

=====
CURRENT FAMILY: 1.0.0
CONFIG VERSION: 1.20.0

; NIC device
BEGIN DEVICE
  DEVICENAME: E810_CQDA2_O_SEC_FW
  VENDOR: 8086
  DEVICE: 1592
  SUBVENDOR: 8086
  SUBDEVICE: 0002
  NVM IMAGE: nvmImage.bin [Include the NVM Image File name to be updated with]
  EEPROMID: 80003FFF [Mention ETrack ID of NVM Image that need to be updated with]
  SKIP NETLIST: FALSE
  IMAGE DOWNGRADE: TRUE
  RESET TYPE: REBOOT
  CURRENT GFID: 0157-1590
  ORIGINAL GFID: 0157-1590
  REVISION: 02
; REPLACES: 80003D96 [Optional when 4 part ID is used above, Multiple Etrack IDs
                      can be entered separated with space]
END DEVICE
=====

```

### 6.3.2 On X710/XXV710/XL710 and X550 Devices

1. Include the custom NVM Image binary file under the same folder as the *nvmupdate.cfg* file and *nvmupdate64e* executable file.
2. Open the *nvmupdate.cfg* file as text file.
3. Copy and paste one of the device blocks (or use the example in [Section 6.1](#)) and update following information for custom NVM image update.
  - a. Custom NVM Image binary file name in **NVM IMAGE** field.
  - b. ETrack ID (in the **EEPROMID** field) of the custom NVM Image listed in **NVM IMAGE** field. This is the image that the device will be update to.
  - c. ETrack ID (in **REPLACES** field) of NVM Image that an update will be allowed from.

**Note:** When editing the *nvmupdate.cfg* file, you must ensure the ETrack ID in the **REPLACES** field and the **EEPROMID** field are the same type of image and are both created for the device that is being updated. For example, in X710/XXV710/XL710, a device with CFG\_ID 2.4 should be updated with an image with CFG\_ID 2.4.

- d. **DEVICE**, **VENDOR**, **SUBDEVICE**, and **SUBVENDOR** must be set correctly to match the device required to update. **SUBDEVICE** and **SUBVENDOR** are optional when **EEPROMID** is used.

OROM update can be skipped by including the line `SKIP OROM: TRUE`. Use **bootutil** to update the OROM if necessary. The remaining fields, including **CURRENT FAMILY**, **CONFIG VERSION**, **DEVICENAME**, and **RESET TYPE**, can typically be left as is.

4. Run the *nvmupdate64e* executable file.

Following is an example of Device block in the configuration file. This includes the minimum fields required for an update. The fields listed in red should be updated:

```
=====
CURRENT FAMILY: 12.1.1
CONFIG VERSION: 1.7.0

BEGIN DEVICE
  DEVICENAME: Intel x540 Adapter
  VENDOR: 8086
  DEVICE: 10C9
  NVM IMAGE: nvmImage.bin [Include the NVM Image File name to be updated with]
  SKIP OROM: TRUE
  EEPID: 800007A9 [Mention ETrack ID of NVM Image that need to be updated with]
  REPLACES: 80000692 [Looks for Etrack ID of NVM Image that need to be replaced,
                    Multiple Etrack IDs can be entered separated with space]

  RESET TYPE: POWER
END DEVICE
=====
```

## 7.0 Summary

Updating the NVM and network driver can increase performance, manageability, and reliability of the E810, X710/XXV710/XL710, and X550 Converged Network Adapters. The update process has a built-in integrity feature to ensure that only Intel-approved firmware code is able to be updated after manufacturing. This procedure is performed each time an attempt is made to update one of the protected modules.

Intel Customer Support Services offers a broad selection of technical and customer support programs. For more information, contact your local Intel representative. Service and availability may vary by country.

For more information on the Intel® Ethernet E810 adapter family, go to the following link:

- <https://www.intel.com/content/www/us/en/architecture-and-technology/ethernet.html>

For more information on the Intel® Ethernet X710/XXV710/XL710 adapter family go to the following links:

- <http://www.intel.com/content/www/us/en/network-adapters/converged-network-adapters/ethernet-x710.html>
- <http://www.intel.com/content/www/us/en/embedded/products/networking/ethernet-controller-xl710-family.html>
- <http://www.intel.com/content/dam/www/public/us/en/documents/product-briefs/ethernet-x710-brief.pdf>
- <http://www.intel.com/content/dam/www/public/us/en/documents/product-briefs/xl710-10-40-gbe-controller-brief.pdf>
- <https://www.intel.com/content/www/us/en/ethernet-products/network-adapters/ethernet-xxv710-brief.html>

For more information on the Intel® Ethernet X550 adapter family go to the following link:

- <https://www.intel.com/content/www/us/en/ethernet-products/converged-network-adapters/ethernet-x550-brief.html>

**NOTE:**        ***This page intentionally left blank.***



## LEGAL

---

No license (express or implied, by estoppel or otherwise) to any intellectual property rights is granted by this document.

This document (and any related software) is Intel copyrighted material, and your use is governed by the express license under which it is provided to you. Unless the license provides otherwise, you may not use, modify, copy, publish, distribute, disclose or transmit this document (and related materials) without Intel's prior written permission. This document (and related materials) is provided as is, with no express or implied warranties, other than those that are expressly stated in the license.

Intel disclaims all express and implied warranties, including without limitation, the implied warranties of merchantability, fitness for a particular purpose, and non-infringement, as well as any warranty arising from course of performance, course of dealing, or usage in trade.

This document contains information on products, services and/or processes in development. All information provided here is subject to change without notice. Contact your Intel representative to obtain the latest forecast, schedule, specifications and roadmaps.

The products and services described may contain defects or errors which may cause deviations from published specifications.

Copies of documents which have an order number and are referenced in this document may be obtained by calling 1-800-548-4725 or by visiting [www.intel.com/design/literature.htm](http://www.intel.com/design/literature.htm).

Intel and the Intel logo are trademarks of Intel Corporation in the U.S. and/or other countries.

Other names and brands may be claimed as the property of others.

© 2015-2020 Intel Corporation.